

RackView QUICK START



Step-by-Step Instructions

1U Rack Mounted KVM Drawer with KVM Switch Option

⇒ **RV1-KVM15**
1U, 15" LCD

1U Package Contents

- Monitor Keyboard Assembly (1)
- Screw Pack
- Power Supply and Mount
- Power Cords (2)
- Manual

Tools Needed

#2 Phillips Head Screwdriver

Questions?

- If you have any questions or difficulties while installing the RackView unit, call (281) 933-7673 immediately and ask to speak to a Rose Technician.
- One year warranty.



Things to Note

- This installation Quick-Start is for the RackView 1U drawer itself. When RackView includes the Rose KVM switch option, please refer to the switch manual for cable connectivity and configuration.
- There are two ways to install this unit:
Option 1 - You can mount the fully assembled unit into the rack.
Option 2 - You can disconnect the unit and mount each piece separately.

ROSE ELECTRONICS - US HEADQUARTERS

10707 Stancliff Road ■ Houston, Texas 77099 ■ USA
Tel 281-933-7673 ■ Tel 800-333-9343 ■ Fax 281-933-0044 ■ sales@rosel.com

ROSE ELECTRONICS - CANADA

4981 Hwy 7 E, Unit 12A, Ste 255 ■ Markham, Ontario L3R 1N1 ■ CANADA
Tel 905-475-4242 ■ Fax 905-415-1444 ■ canadiansales@rosel.com

ROSE ELECTRONICS - EUROPE

Bourne Works High Street ■ Collingbourne Ducis
Marlborough Wiltshire SN8 3EH ■ UNITED KINGDOM
Tel +44 (0) 126 485 0574 ■ Fax +44 (0) 126 485 0529 ■ europesales@rosel.com

ROSE ELECTRONICS - BENELUX

Albert Plesmanweg 121-141 ■ Rotterdam 3088 GC ■ ZUID HOLLAND
Tel +31 (0) 6-53481450 ■ Fax +31 (0) 10-2833235 ■ beneluxsales@rosel.com

ROSE ELECTRONICS - GERMANY

Lise-Meitner-Strasse 1-7 ■ 24223 Ralsdorf ■ GERMANY
Tel +49-430-7900-170 ■ Fax +49-430-7900-171 ■ germansales@rosel.com

ROSE ELECTRONICS - ASIA PACIFIC

PO Box 3184 ■ Robina T.C. ■ Queensland 4230 ■ AUSTRALIA
Tel +617 5575 9028 ■ Fax +617 5575 9352 ■ asiapacificsales@rosel.com



WWW.ROSEL.COM

INSTALLATION OPTION 1 - Fully Assembled




Step 1

Remove the tray from packaging.




Step 2

Loosen rear finger bracket and cable retractor screws. Next slightly angle unit to fit through rack.




Step 3

Cowl is preset. Do not remove unless absolutely necessary.
Loosely mount rail brackets to rails. Do not put screw in center hole.



Step 3

Fully extend rails.




Step 3

Cowl is preset. Do not remove unless absolutely necessary.
Loosely mount rail brackets to rails



Do not put screw in center hole.




Step 4

Adjust rear finger brackets to fit rackrail. Tighten mounting screws. Tighten rear finger brackets and cable retractor



Step 4

Guide monitor keyboard assembly into slides, pushing unit all the way to back of rack.



Step 5


Tighten rear finger bracket screws. Then install and tighten cable retractor screw.

INSTALLATION OPTION 2 - Unassembled



Step 1

Remove the tray from packaging.



Step 2

Remove cable retractor screws and loosen rear finger bracket screws. Facing rear of shelf remove slide from rail. Push down metal locks (on both sides) to release the full extension slides.



Step 6

Adjust rear finger brackets to fit rackrail. Once the shelf is seated, tighten the screws on the mounting rails.