Trader Switch Installation and Operations

Introduction


Raritan's TraderSwitch allows users to operate a Sun Workstation and a PS/2 PC from a single Sun keyboard and mouse. It is designed to be highly reliable and ergonomically integrated into a modern office environment.


Installation


- 1. Connect monitors to the Sun Workstation and the PC.
- Connect a Sun keyboard and mouse cable to the TraderSwitch keyboard port (A).
- Connect the Sun keyboard and mouse cable (CTSS20) from TraderSwitch Sun Channel (B) to the Sun Workstation keyboard port.
- Connect the PC keyboard and mouse cable (CTSP20U) from TraderSwitch PC Channel (C) to the PC keyboard and mouse ports.
- **5.** Power ON first the Sun Workstation, and then the PC.
- If necessary, connect the optional DC power supply to the TraderSwitch (D).

Operation

- Use TraderSwitch front panel buttons to switch between the Sun Workstation and the PC.
 - Push Sun button for Sun Workstation (E)
 - Push PC button for PC (F)
- Or, use the designated keys as shown on the Sun keyboard to switch between the Sun Workstation (G) and the PC (H).
- Optionally, you can activate the beeping sound when switching channels.
 - Press either the Sun or the PC button on the TraderSwitch front panel, and hold for at least four seconds.
 - If you hear two beeps, the beeping sound is ON.
 - If you hear one beep, the beeping sound is OFF.







Specifications

TS2

Dimensions 10.55" (W) x 7.87" (D) x 1.75" (H)

1.62 kg (3.6 lbs)

Power Powered by connected computers

Operating Temp. $0-50^{\circ}$ C (32–122 $^{\circ}$ F)

Cables

CTSS20 6.5' cable for Sun KB and mouse CTSP20U 6.5' cable for PC KB and mouse

Optional DC

Adapter 6V/500mA Adapter (DC6500U)

One Year Warranty

E-mail: sales.europe@raritan.com

http://www.raritan.com

Raritan Computer Japan, Inc.